2622

Please type a plus sign (+) inside this box ⟶ +

TRANSMITTAL FORM

(to be used for all correspondence after initial filing)

Application Number	10/046,639
Filing Date	October 26, 2001
First Named Inventor	Li, Bin
Group Art Unit	
Examiner Name	

Total Number of Pages in This Submission	2	Attorney Docket Number	020510-002000US

ENCLOSURES *(check all that apply)*

- [ ] Fee Transmittal Form
  - [ ] Fee Attached
- [ ] Amendment / Response
  - [ ] After Final
  - [ ] Affidavits/declaration(s)
- [ ] Extension of Time Request
- [ ] Express Abandonment Request
- [ ] Information Disclosure Statement
- [x] Certified Copy of Priority Document(s) (CA App. No. 2,324,574)
- [ ] Response to Missing Parts/ Incomplete Application
  - [ ] Response to Missing Parts under 37 CFR 1.52 or 1.53

- [ ] Assignment Papers *(for an Application)*
- [ ] Drawing(s)
- [ ] Licensing-related Papers
- [ ] Petition Routing Slip (PTO/SB/69) and Accompanying Petition
- [ ] Petition to Convert to a Provisional Application
- [ ] Power of Attorney, Revocation Change of Correspondence Address
- [ ] Terminal Disclaimer
- [ ] Request for Refund
- [ ] CD, Number of CD(s)

Remarks	The Commissioner is authorized to charge any additional fees to Deposit Account 20-1430.

- [ ] After Allowance Communication to Group
- [ ] Appeal Communication to Board of Appeals and Interferences
- [ ] Appeal Communication to Group *(Appeal Notice, Brief, Reply Brief)*
- [ ] Proprietary Information
- [ ] Status Letter
- [x] Other Enclosure(s) *(please identify below):*
  Return Postcard

RECEIVED

JUN 0 6 2002

Technology Center 2600

SIGNATURE OF APPLICANT, ATTORNEY, OR AGENT

Firm and Individual name	Townsend and Townsend and Crew LLP	
	Charles Hamilton	Reg. No. 42,624
Signature	*[signature]*	
Date	May 21, 2002	

CERTIFICATE OF MAILING

I hereby certify that this correspondence is being deposited with the United States Postal Service with sufficient postage as first class mail in an envelope addressed to: Assistant Commissioner for Patents, Washington, D.C. 20231 on this date:

5/21/02

Typed or printed name	M. Diane Dube		
Signature	*M. Diane Dube*	Date	5/21/02

PA 3223836 v1

#4

Office de la propriété
intellectuelle
du Canada

Canadian
Intellectual Property
Office

Un organisme
d'Industrie Canada

An Agency of
Industry Canada

OIPE JC154
MAY 3 1 2002
PATENT & TRADEMARK OFFICE

Bureau canadien
des brevets

Certification

Canadian Patent
Office

Certification

La présente atteste que les documents
ci-joints, dont la liste figure ci-dessous,
sont des copies authentiques des docu-
ments déposés au Bureau des brevets.

This is to certify that the documents
attached hereto and identified below are
true copies of the documents on file in
the Patent Office.

Specification as originally filed with Application Patent Serial No: **2,324,574**, on
October 26, 2000, by CATENA NETWORKS CANADA INC., assignee of Bin Li,
Alberto Ginesi and Song Zhang, for An Optimum Allocation Algorithm for Reed-
Solomon Coded Data for ADSL.

RECEIVED

JUN 0 6 2002

Technology Center 2600

Agent certificateur/Certifying Officer

February 26, 2002

Date

Canada

OPIC CIPO

AN OPTIMAL BIT ALLOCATION ALGORITHM FOR REED-SOLOMON CODED DATA FOR DSL

BACKGROUND OF INVENTION

5 It is well known that the performance of an xDSL (digital subscriber line) or more specifically ADSL modem is generally limited by cross-talk. In order to improve the performance, error-correcting codes such as the Reed-Solomon (RS) code is used in ADSL modem signals. The performance improvement not only depends on the RS code parameters such as the code-word length and redundant length, but also depends on the

10 transmission environment such as signal-to-noise ratio distribution over the carriers. For different transmission environments, a best selected RS code, which can maximize the transmission rate, is different to a best selected RS code that can, at the same time, minimize the transmitted power. Furthermore the selection of the best code in either circumstance is also very difficult. The subject invention attempts to mitigate at least one

15 or more of the above disadvantages.

DESCRIPTION OF INVENTION

20 The present invention provides a bit allocation algorithm for RS coded data. The algorithm will find the best RS code that can maximize the transmitted data rate and minimize the transmitted power. Other constraints such as impulse noise protection and max latency can be added as well.

25 The bit allocation algorithm is described follows.

1. Pre-calculate the gross coding gain of RS code with different code-word length N (in byte) and parity length R (in byte), and save them in a table or expressed as a mathematical expression such as polynomial expression.

30 2. Calculate the total number of allocated bits without RS code by

$$b_0 = \sum_{k=1}^{M} \log_2\left(1 + \frac{SNR_k}{\Gamma \cdot \gamma}\right) \qquad (1)$$

1

where SNR_k is the signal-to-noise ratio for kth sub carrier, Γ is the energy gap associated with QAM transmission and for a given Bit Error Rate (BER), γ is the required margin and finally M is the number of used bins.

5 3. Initialize the gross coding gain $G = G_{min}$.

4. According to the gross coding gain G, calculate the total number of allocated bits as described in refrence [1]

$$b = \sum_{k=1}^{M} \log_2\left(1 + \frac{SNR_k}{\Gamma \cdot \gamma / G}\right)$$ (2)

10

5. Find RS codes (in the table obtained in step 1 or the mathematical expression) with such $N = bS$ (where $S \in \{1,2,4,8,16\}$ for ADSL G.lite standard [3]) and R that can provide this gross coding gain or larger. If such code exits, then calculate the information bits $b' = b - R/S$ and restore the parameters (N, R, S, b'). Note that the delay and other

15 requirements such as impulse noise protection can limit the selection of S and R. For example, if protection against an error burst longer than P bytes is desired, the constraint to be used is R*D/2> P [2], where D is the interleaver depth of the inner interleaver associated with the RS code. If a max latency of the system is to be less than Lmax ms,

then the constraint to be used is $x + \frac{(S-1)}{4} + \frac{S \cdot D}{4} < L\max$ [3], where x is the constant

20 system delay in ms.

6. Increase G by Δ, and go back to step 4 until G reaches the maximum value G_{max}.

7. Select the parameters (N, R, S, b') which corresponds to the maximum information

25 bits b', compare this number with b_0 to make sure that RS improves the capacity, otherwise do not use RS code.

References:

10   [1]   T.Starr, J.M.Cioffi and P.J.Silverman, Understanding Digital Subscriber Line Technology, Prentice Hall 1999

[2]   T.N.Zogakis, P.T.Tong and J.Cioffi, "Performance Comparison of FEC/Interleave Choices with DMT for ADSL", Amati Communications Corp., contribution T1E1.4/93-091

15   [3]   G.992.2 (G.lite): Asymmetrical Digital Subscriber Line (ADSL) Transceiver, ITU, 1999

Claims:

The calculation procedure in the algorithm.

Pre-calculation of gross coding gain of RS code.

Search the RS code through gross coding gain or net coding gain.

5   Choose the RS code parameters with maximum information bits b'.